# **ESDU3121**

# 12 V Unidirectional ESD and **Surge Protection Device**

The ESDU3121 is designed to protect voltage sensitive components from ESD. Excellent clamping capability, low leakage, high peak pulse current handling capability and fast response time provide best in class protection on designs that are exposed to ESD. Because of its small size, it is suited for use in cellular phones, tablets, MP3 players, digital cameras and many other portable applications where board space comes at a premium.



• Low Clamping Voltage

• Low Leakage

• Small Body Outline: 1.0 mm x 0.6 mm

• Protection for the Following IEC Standards:

IEC61000-4-2 Level 4: ±30 kV Contact Discharge IEC61000–4–5 (Lightning): 8.5 A (8/20 μs)

• These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

# **Typical Applications**

• Power Line Protection

• GPIO Protection

**Table 1. MAXIMUM RATINGS** 

Rating		Symbol	Value	Unit
IEC 61000-4-2 (ESD) Contact			±30	kV
	Air		±30	
Operating Junction Temperature Range		$T_J$	-65 to + 150	°C
Storage Temperature Range		T <sub>STG</sub>	-65 to + 150	°C
Minimum Peak Pulse Current		I <sub>PP</sub>	8.5	Α

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.



# ON Semiconductor®

www.onsemi.com



CASE 714AB

**DIAGRAM** 



**MARKING** 

YK = Specific Device Code

= Date Code



#### ORDERING INFORMATION

Device	Package	Shipping <sup>†</sup>
ESDU3121MXT5G	X2DFN2 (Pb-Free)	8000 / Tape & Reel


†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

## **Table 2. ELECTRICAL CHARACTERISTICS**

 $(T_A = 25^{\circ}C \text{ unless otherwise noted})$ 

, ,				
Symbol	Parameter			
I <sub>PP</sub>	Maximum Reverse Peak Pulse Current			
V <sub>C</sub>	Clamping Voltage @ I <sub>PP</sub>			
V <sub>RWM</sub>	Working Peak Reverse Voltage			
I <sub>R</sub>	Maximum Reverse Leakage Current @ V <sub>RWM</sub>			
V <sub>BR</sub>	Breakdown Voltage @ I <sub>T</sub>			
I <sub>T</sub>	Test Current			

<sup>\*</sup>See Application Note AND8308/D for detailed explanations of datasheet parameters.



**Uni-Directional Surge Protection** 


**Table 3. ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C unless otherwise specified)

Parameter	Symbol	Conditions	Min	Тур	Max	Unit
Reverse Working Voltage	$V_{RWM}$	I/O Pin to GND			12	V
Breakdown Voltage	$V_{BR}$	I <sub>T</sub> = 1 mA, I/O Pin to GND	14.1	15	15.8	V
Reverse Leakage Current	I <sub>R</sub>	@ V <sub>RWM</sub> , I/O Pin to GND			0.1	μΑ
Reverse Peak Pulse Current	I <sub>PP</sub>	IEC-61000-4-5 (8x20 μs)	8.5			Α
Clamping Voltage 8x20 μs Waveform per Figure 3	V <sub>C</sub>	I <sub>PP</sub> = 8.5 A		20.3	22	V
Dynamic Resistance	R <sub>DYN</sub>	I/O Pin to GND, IEC-61000-4-5 (8x20 μs)		0.70		Ω
Junction Capacitance	CJ	V <sub>R</sub> = 0 V, f = 1 MHz		55		pF

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

## **ESDU3121**

#### **TYPICAL CHARACTERISTICS**



#### Transmission Line Pulse (TLP) Measurement

Transmission Line Pulse (TLP) provides current versus voltage (I–V) curves in which each data point is obtained from a 100 ns long rectangular pulse from a charged transmission line. A simplified schematic of a typical TLP system is shown in Figure 7. TLP I–V curves of ESD protection devices accurately demonstrate the product's ESD capability because the 10s of amps current levels and under 100 ns time scale match those of an ESD event. This is illustrated in Figure 8 where an 8 kV IEC 61000–4–2 current waveform is compared with TLP current pulses at 8 A and 16 A. A TLP I–V curve shows the voltage at which the device turns on as well as how well the device clamps voltage over a range of current levels. For more information on TLP measurements and how to interpret them please refer to AND9007/D.




Figure 7. Simplified Schematic of a Typical TLP System




Figure 8. Comparison Between 8 kV IEC 61000-4-2 and 8 A and 16 A TLP Waveforms

#### **ESD Voltage Clamping**

For sensitive circuit elements it is important to limit the voltage that an IC will be exposed to during an ESD event to as low a voltage as possible. The ESD clamping voltage is the voltage drop across the ESD protection diode during an ESD event per the IEC61000-4-2 waveform. Since the IEC61000-4-2 was written as a pass/fail spec for larger systems such as cell phones or laptop computers it is not clearly defined in the spec how to specify a clamping voltage at the device level. ON Semiconductor has developed a way to examine the entire voltage waveform across the ESD protection diode over the time domain of an ESD pulse in the form of an oscilloscope screenshot, which can be found on the datasheets for all ESD protection diodes. For more information on how ON Semiconductor creates these screenshots and how to interpret them please refer to AND8307/D.

# IEC 61000-4-2 Spec.

Level	Test Volt- age (kV)	First Peak Current (A)	Current at 30 ns (A)	Current at 60 ns (A)
1	2	7.5	4	2
2	4	15	8	4
3	6	22.5	12	6
4	8	30	16	8




Figure 9. IEC61000-4-2 Spec






Figure 10. Diagram of ESD Test Setup




### X2DFN2 1.0x0.6, 0.65P CASE 714AB **ISSUE B**

**DATE 21 NOV 2017** 







**BOTTOM VIEW** 

- NOTES:
  1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
  2. CONTROLLING DIMENSION: MILLIMETERS.
  3. EXPOSED COPPER ALLOWED AS SHOWN.

	MILLIMETERS			
DIM	MIN	NOM	MAX	
Α	0.34	0.37	0.40	
A1		0.03	0.05	
b	0.45	0.50	0.55	
D	0.95	1.00	1.05	
Е	0.55	0.60	0.65	
е	0.65 BSC			
L	0.20	0.25	0.30	


# **GENERIC MARKING DIAGRAM\***



XX = Specific Device Code

M = Date Code

# **RECOMMENDED SOLDER FOOTPRINT\***



DIMENSIONS: MILLIMETERS

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " •" may or may not be present. Some products may not follow the Generic Marking.

DESCRIPTION:	X2DFN2 1.0X0.6, 0.65P	PAGE 1	OF 2
NEW STANDARD:		"CONTROLLED COPY" in red.	
STATUS:	ON SEMICONDUCTOR STANDARD	accessed directly from the Document Repository. Versions are uncontrolled except when stamp	
DOCUMENT NUMBER:	98AON98172F	Electronic versions are uncontrolled except	

ON Semiconductor®



**DOCUMENT NUMBER:** 98AON98172F

PAGE 2 OF 2

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, its patent rights nor the rights of others. Scilled products are not designed, intended or authorized for use as components in a systems intended to support or surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

 Semiconductor Components Industries, LLC, 2017 November, 2017 - Rev. B **714AB** 

ON Semiconductor and the are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor and see no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and

#### **PUBLICATION ORDERING INFORMATION**

LITERATURE FULFILLMENT:
Email Requests to: orderlit@onsemi.com

ON Semiconductor Website: www.onsemi.com

TECHNICAL SUPPORT North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support:

Phone: 00421 33 790 2910

For additional information, please contact your local Sales Representative